



OEX508

8-Relay Expansion Card



EOX508 is an output expander that allows adding 8 hardwired relays to the FORCE Security System.

The EOX508 can be powered by PIMA's PS-2 power supply.

The OEX508 interfaces with the BUS and is supplied mounted in a plastic enclosure.

Features

- 8 relay outputs
- Communicates using PIMA propriety ForceBus
- Card and Communication status LEDs
- Tamper switch protection against opening and removal
- Interfacing with the BUS

Technical specifications

- Relays: 1A, NO/NC/COM
- Baud rate: 19,200bps
- Voltage levels: 0,+12V
- Differential, Half Duplex
- Terminal block connections
- Plastic enclosure
- Operating Voltage Range: 9-14VDC
- Current Consumption: @13.8V-31±10 mA (all relays are OFF)
- PS-2:
 - Voltage (max): 15VDC
 - Indication inputs: AC loss, Low Battery
 - Molex connector
- Operating temperature range: -10°C to +55°C

©2017 Pima Electronic Systems. All rights reserved

Manufactured by:

PIMA Electronic Systems Ltd.

WWW.PIMA-ALARMS.COM

5 Hatzoref Street, Holon 5885633, ISRAEL

Tel: +972.3.6506414 Fax: +972.3.5500442

Email: support@pima-alarms.com

Doc no. SPC-8500028, Revision: Dec 2017

