

RMC

Wireless Remote Control



The RMC is a wireless remote control designed for the **FORCE** and **FORCE Lite** intruder alarm systems.

The RMC can be used for arming and disarming the alarm system, and to activate devices, such as lights and electric gates. The detector's LED illuminates on every transmission and when its battery is low.

PIMA Electronic Systems' portfolio includes a wide selection of hardwired and wireless detectors, sensors and sirens for both security and safety purposes. Our products are developed with uncompromising quality, ease of installation, and operation experience.

PIMA's wireless detectors integrate the FastLink technology, an advanced wireless detection technology using true, 128-bit AES encryption that ensures maximum wireless security.

PIMA's detectors are a perfect solution for the business as well as for the home markets.

PIMA's alarm systems interface with a wide selection of expanders and peripherals, enabling the customer to expand the system as needed.

The **FORCE** and **FORCE Lite** alarm systems interface with a wide selection of expanders and peripherals, enabling the customer to expand the system as needed.

Features

- Elegant design in black or white
- Supplied with a keychain
- Battery powered with low battery reporting
- Transmission and low battery LED
- Panic button

Technical specifications

- Transmission:
 - Frequency (MHz):
 - RMC143: 433.92
 - RMC187: 868.95
 - Output: 10mW
 - Bandwidth: 100KHz
 - Modulation: FM
- One-way
- Range: 500m in open space¹
- Battery: 1X CR2032, 3V, Lithium.
- Battery Life Expectancy: Up to 3 Years (Normal Usage)

¹ Walls or metal may reduce actual operating range

- Dimensions: 5.5 X 3.5 X 1.2 cm
- Weight (excluding battery): 35gr
- CE compliance
- Operating temperature: -10 to +50 °C
- Humidity (max.): 93% R.H., non-condensing.

Ordering Information

- RMC143, white, P/N: 8833004
- RMC143, black, P/N: 8833008
- RMC187, white, P/N: 8833012
- RMC187, black, P/N: 8833013



All rights reserved © 2019 Pima Electronic Systems Ltd.

For product information
www.pima-alarms.com

Manufactured by:
PIMA Electronic Systems Ltd.
5 Hatzoref Street, Holon 5885633, Israel
Tel: +972.3.6506444
Fax: +972.3.5500442
Email: support@pima-alarms.com

Doc no. SPC-8833004, Revision: 10-2019