





The VPT/VPR500 is a PSTN module of the **VISION** wireless alarm system, which allows it to connect to PSTN network. The VPT500 has Line IN/Line OUT terminal block connector, and the VPR model has RJ11 sockets. A green LED supplies off-hook indication.

PIMA Electronic Systems' portfolio includes a wide selection of hardwired and wireless detectors, sensors and sirens for both security and safety purposes. Our products are developed with uncompromising quality, ease of installation, and operation experience.

PIMA's wireless detectors integrate the FastLink technology, an advanced wireless detection technology using true, 128-bit AES encryption that ensures maximum wireless security.

PIMA's detectors are a perfect solution for the business as well as for the home markets.

The **VISION** alarm system interface with a wide selection of receivers and peripherals, enabling the customer to expand the system as needed.

Installation and Wiring




Disconnect from AC and battery power before installation.

- 1. Open the VISION's enclosure: release the two screws at the bottom, and remove the lid.
- 2. Install the PSTN module on its designated connector (marked in red in the image below).



- 3. Connect the phone line between the Line IN terminals and the phone socket.
- 4. Connect other phone sets to the Line OUT terminals. Make sure the *VISION* is the first device to connect to the phone line.



- 5. Close the lid and fasten the screws.
- 6. Connect to power.



Indication LED

A green LED on the module (marked with a red arrow in the image below) indicates when the module is off-hook (communication in progress).



Technical Specifications

Dimensions: 70 X 50 X 12 mm

Weight: ~22gr

Operating temperature: -10 to +50 °C

• Humidity (max.): 93% R.H., non-condensing.

Ordering Information

VPT500 (Terminal block) P/N: 8300081
VPR500 (RJ11 sockets) P/N: 8300082





For product information www.pima-alarms.com

All rights reserved © 2020 Pima Electronic Systems Ltd.

Manufactured by:

PIMA Electronic Systems Ltd.

5 Hatzoref Street, Holon 5885633, Israel

Tel: +972.3.6506414 Fax: +972.3.5500442

Email: support@pima-alarms.com

Doc no. SPC-8300081, Revision: 2-2020